Visit product page



FORTIUS STAND ALONE

L005009

512 Dmx channels stand alone interface , Pro DMX + Studio DMX compatible 2x512 Out PC and Stand Alone channels (using no PC)

TECHNICAL DETAILS

Technical Details

- Pro DMX + LED Player + Studio DMX compatible
- 30 minutes loop of Audio and Video Timeline with Pro DMX
- 1 ARTNET Universe
- Windows, MAC Os X (10.6 and +) and Linux (64) compatible
- 2x512 Out PC and Stand Alone channels (using no PC)
- Splitter mode 2x512 out
- DMX in record and DMX in triggers (PC)
- DMX merging signal in Stand Alone (in/out mode)
- 16 bits and fine channel management in Stand Alone
- Automatic Scene Recovery if the power is accidently cut off
- Cross Fade time between scenes in Stand Alone
- Scene Speed, manual color (RGBW), page, Dimmer modes
- 8 trigger buttons with blue LED
- 4 buttons for Mode, valid, + and -
- 7 contact triggers to 5V (On, On/Off, Release or Restart scenes)
- Real Time Clock triggers for scenes (Day, Week, Month, Year)
- RS232 triggers in PC and Stand Alone
- Master/Slave mode to interconnect and synchronize up to 32 interfaces in Stand Alone (32768 dmx channels without pc use)
- Infrared Triggers via an external module + IR remote (Optional)
- 4 Mb of internal memory (min. capacity: 6,000 steps/512 ch)

• Power input of 9 to 36V. (standard DC connector)
• Black housing with 4 mounting holes, ABS Plastic
• Mini USB 2.0 - 5V. DC
• 3 Pins XLR (XLR5 optional)
• RJ45 connectors for I/O and triggers
• Dimensions and Weight: H: 4 cm ; W: 14 cm ; L: 9 cm ; 0.2 Kgs
• Operating temperatures: -25 to +70 Cº
• Certifications: CE, RoHS

Software Download

Download software for Windows and Mac.

PHOTOS





ADDITIONAL INFO

Software download links are :

Win: http://www.prodmx.com/filedownload/Update/fos_setup.exe

Mac: http://www.prodmx.com/filedownload/Update/fos_setup.pkg.zip

Updated FOS fixtures library